

Technical Accessory Guides (TAGs)

For Associates, Resellers, ISVs and Alliance Partners

Global



Version: Active-Only

Will only show products that are known to be available for sale

Need to provide an update or change?

Contact <mailto:pgw786@zebra.com>



For Internal Use by
PartnerConnect Members Only



WT6400 Technical Accessory Guide




Does NOT include accessories for WT6000/WT6300. See separate guides for WT6000/WT6300 accessories.

NOTE: This document is only for general reference. Solutions Pathway and related PMBs should be used for product availability, pricing, and final solution selection.




* Zebra does not endorse or specifically recommend any **third-party products, accessories, or hardware**. ZEBRA DISCLAIMS ANY AND ALL LIABILITY, INCLUDING ANY EXPRESS OR IMPLIED WARRANTIES, WHETHER ORAL OR WRITTEN, FOR SUCH THIRD PARTY PRODUCTS, ACCESSORIES, OR HARDWARE. THE CUSTOMER ACKNOWLEDGES THAT NO REPRESENTATION HAS BEEN MADE BY ZEBRA AS TO THE FITNESS OF THE THIRD-PARTY PRODUCTS, ACCESSORIES, OR HARDWARE FOR THE CUSTOMER'S INTENDED PURPOSE.


Cradles and Charging

Single Device Cradles




Part Number	Picture	Description	Notes	Required Items
CRD-WT5X6-1S1BC-01		Single Slot Charge-Only ShareCradle	<ul style="list-style-type: none"> ► Supports terminal and spare battery charging ► LED notification of spare battery charging status. ► Connects to 2-pin charge contacts on side of WT6400. 	<ul style="list-style-type: none"> ► Power Supply (PWR-BGA12V50W0WW and CBL-DC-388A1-01) ► AC Line Cord (23844-00-00F or country specific version)

Multi-Device Cradles

Part Number	Picture	Description	Notes	Required Items
CRD-WT5X6-5S5BC-01		5-Slot Charge Only Cradle w/Spare Battery Charging	<ul style="list-style-type: none"> ► Charges 5 devices and 5 spare batteries ► Can also be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01) ► Connects to 2-pin charge contacts on side of WT6400. 	<ul style="list-style-type: none"> ► DC Line Cord (CBL-DC-382A1-01) ► Power Supply (PWR-BGA12V108W0WW) ► AC Line Cord (23844-00-00F or country specific version)
CRD-WT5X6-10SC-01		10-Slot Charge Only Cradle	<ul style="list-style-type: none"> ► Charges 10 devices ► Does not charge spare batteries ► Can also be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01) ► Connects to 2-pin charge contacts on side of WT6400. 	<ul style="list-style-type: none"> ► DC Line Cord (CBL-DC-382A1-01) ► Power Supply (PWR-BGA12V108W0WW) ► AC Line Cord (23844-00-00F or country specific version)
CRD-WT64-5S5BE-01		WT6400 5-Slot Ethernet + Charge Cradle w/Spare Battery Charging	<ul style="list-style-type: none"> ► Allows Ethernet speeds up to 1 Gb ► Charges 5 WT6400 devices and 5 spare batteries. ► Not compatible with WT5400. ► Can also be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01) ► Connects to rugged I/O connector on side of WT6400. 	<ul style="list-style-type: none"> ► DC Line Cord (CBL-DC-382A1-01) ► Power Supply (PWR-BGA12V108W0WW) ► AC Line Cord (23844-00-00F or country specific version)




BRKT-SCRD-SMRK-01		Multi-Slot Wall/Rack Mount Bracket	<ul style="list-style-type: none"> ► Allows for rack and wall mounting of one 5-Slot, 10-Slot, or 20-Slot Charger. Also can be used to mount up to four 4-Slot Battery Chargers or Single-Slot Cradles ► Bracket can be mounted on standard 19" network rack or on a wall. ► Cable routing slots & removable power supply holder tray. ► Adjustable tabs & screw mounts for easy hanging/installation. ► Adjustable orientations - horizontal, vertical, angled. ► See the Bluetooth-Generic Accessories TAG for info on 3rd party Network Racks that can be used for mounting this bracket. 	
-------------------	---	------------------------------------	--	--

Misc. Cradle Accessories




Part Number	Picture	Description	Notes	Required Items
CRDCUP-W5X6-1DB-01 (single cup)		WT5400/WT6400 Charge-Only ShareCradle Cup Conversion Kit, Device + Battery	<ul style="list-style-type: none"> ► Can be used to replace a legacy WT6000/WT6300 series cradle cup when migrating from legacy WT6X to WT5400/WT6400. ► Can also be used to replace a damaged cradle cup. ► Cup will charge one device and one spare battery. ► Only compatible with cradles that use ShareCradle design (i.e. TC5X series). ► Kit includes: <ul style="list-style-type: none"> - ShareCradle Cup - screw for attaching cup to cradle 	
CRDCUP-W5X6-2D-01 (single cup)		WT5400/WT6400 Charge-Only ShareCradle Cup Conversion Kit, 2xDevice	<ul style="list-style-type: none"> ► Can be used to replace a legacy WT6000/WT6300 series cradle cup when migrating from legacy WT6X to WT5400/WT6400. ► Can also be used to replace a damaged cradle cup. ► Cup will charge two devices. ► Only compatible with cradles that use ShareCradle design (i.e. TC5X series). ► Kit includes: <ul style="list-style-type: none"> - ShareCradle Cup - screw for attaching cup to cradle 	
CRDCUP-WT64-1DE-01 (single cup)		WT6400 Charge/Communication ShareCradle Cup Conversion Kit, Device + Battery	<ul style="list-style-type: none"> ► Can be used to replace a legacy WT6000/WT6300 series cradle cup when migrating from legacy WT6X to WT6400. ► Can also be used to replace a damaged cradle cup. ► Cup will charge one device, one spare battery and also provide Ethernet communication for the device. ► Only compatible with cradles that use ShareCradle design (i.e. TC5X series). ► Kit includes: <ul style="list-style-type: none"> - ShareCradle Cup - screw for attaching cup to cradle 	

Battery Charging

Part Number	Picture	Description	Notes	Required Items
-------------	---------	-------------	-------	----------------





SAC-WT5X6-4SC-01		4-Slot Battery Charger	<ul style="list-style-type: none"> ► Charges up to 4 Spare Batteries ► Up to 4 Battery Chargers can be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01) 	<ul style="list-style-type: none"> ► Power Supply (PWR-BGA12V50W0WW and CBL-DC-388A1-01) ► AC Line Cord (23844-00-00P or country specific version)
SAC-WT5X6-20SC-01		20-Slot Battery Charger	<ul style="list-style-type: none"> ► Charges up to 20 Spare Batteries ► Can be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01) 	<ul style="list-style-type: none"> ► DC Line Cord (CBL-DC-382A1-01) ► Power Supply (PWR-BGA12V108W0WW) ► AC Line Cord (23844-00-00P or country specific version)
CRDCUP-W5X6-4B-01		4-Slot Battery Charger Conversion Kit	<ul style="list-style-type: none"> ► Typically used to swap out a legacy WT6000/WT6300 series Battery Charger. ► Will convert one legacy WT6000/WT6300 4-Slot Battery Charger (SAC-NWTRS-4SCH-01) or order five kits to convert a legacy WT6000/WT6300 20-Slot Battery Charger (SAC-NWTRS-20SCH-01). 	




Communication Cables





Part Number	Picture	Description	Notes	Required Items
CBL-NGWT-USBCHG-01		Snap-on USB Communication/Charging Cable	<ul style="list-style-type: none"> ► Attaches to one of the accessory ports on WT6400 ► Cable can power device from USB connector or via power supply using pigtail barrel jack connector on cable. 	To power via barrel jack pigtail connector: <ul style="list-style-type: none"> ► Power Supply (PWR-BUA5V16W0WW) ► DC Line Cord (CBL-DC-383A1-01) ► AC Line Cord (50-16000-182R)
CBL-NGWT-USBHD-01		WT6X to USB-C Adapter Cable	<ul style="list-style-type: none"> ► Connects to WT6X to accessories with USB-C cable. ► Cable length is 80cm/approx 32 inches. ► Includes 2 alligator clips for attaching cable to clothing. 	
CBL-NGWT-USBH1-01		WT6X to USB-A Adapter Cable	<ul style="list-style-type: none"> ► Connects to WT6X to accessories with USB-A connector (i.e. USB stick, keyboard, mice, etc.). ► NOTE: This is a custom product. Please work with your Zebra representative to obtain Product Management approval if you would like to order this item. 	

Soft Goods - Cases/Holsters

Wrist Mount - single dial				
Part Number	Picture	Description	Notes	Required Items
SG-WT5X6-WMTSS-01		Wrist Mount (small strap)	<ul style="list-style-type: none"> ► Uses BOA dial-to-fit design which is strong, durable, and easy to use. ► Velcro free design uses non-absorbent materials that can be wiped down. ► Includes Carrier and Small size Wrist Strap (SG-NGWT-WSTPST-01). ► White Dial and accent color on strap identify size as Standard (small/medium). ► Strap length can be adjusted between 128 to 191 mm (approx 5.0 to 7.5") ► It is typical for each user to have their own wrist mount (for hygiene). 	
SG-WT5X6-WMTSL-01		Wrist Mount (large strap)	<ul style="list-style-type: none"> ► Uses BOA dial-to-fit design which is strong, durable, and easy to use. ► Velcro free design uses non-absorbent materials that can be wiped down. ► Includes Carrier and Large size Wrist Strap (SG-NGWT-WSTPLN-01). ► Black Dial and accent color on strap identify size as medium/large. ► Strap length can be adjusted between 164 to 265 mm (approx 6.5 to 10.5") ► It is typical for each user to have their own wrist mount (for hygiene). 	
SG-WT5X6-WMTSX-01		Wrist Mount (extra-large strap)	<ul style="list-style-type: none"> ► Uses BOA dial-to-fit design which is strong, durable, and easy to use. ► Velcro free design uses non-absorbent materials that can be wiped down. ► Includes Carrier and Extra-Large size Wrist Strap (SG-NGWT-WSTPXL-01). ► Blue Dial and accent color on strap identify size as extra-large. ► Strap length is 375 mm (approx 14.75") ► This size strap is typically used in freezer environments where users may be wearing heavy jackets. ► It is typical for each user to have their own wrist mount (for hygiene). 	
SG-NGWT-WSTPST-01		Replacement BOA Wrist Strap (small size)	<ul style="list-style-type: none"> ► White Dial and accent color on strap identify size as small/medium. ► Strap length can be adjusted between 128 to 191 mm (approx 5.0 to 7.5") 	

SG-NGWT-WSTPLN-01		Replacement BOA Wrist Strap (large size)	 <ul style="list-style-type: none"> ► Black Dial and accent color on strap identify size as medium/large. ► Strap length can be adjusted between 164 to 265 mm (approx 6.5 to 10.5") 	
SG-NGWT-WSTPXL-01		Replacement BOA Wrist Strap (extra-large size)	<ul style="list-style-type: none"> ► Blue Dial and accent color on strap identify size as extra-large. ► Strap length can be adjusted between 218 to 375 mm (approx 8.5 to 14.75") 	
Wrist Mount - double dial <i>recommended for use with WT6400 keyboard configs and when using extended capacity battery</i>				
Part Number	Picture	Description	Notes	Required Items
SG-WT5X6-WMTDS-01		Double Dial Wrist Mount (small strap)	<ul style="list-style-type: none"> ► Dual dial arm mount provides increased adjustability - typically used with WT6400 Keyboard configs or devices with Extended Battery. ► Uses dial-to-fit design which is strong, durable, and easy to use. ► Velcro free design uses non-absorbent materials that can be wiped down. ► Includes Carrier and Small size Wrist Strap (SG-WT5X6-WMTDS-01). ► White Dial and accent color on strap identify size as small. ► Strap length can be adjusted between 128 to 191 mm (approx 5.0 to 7.5") ► It is typical for each user to have their own wrist mount (for hygiene). 	

SG-WT5X6-WMTDL-01		Double Dial Wrist Mount (large strap)	<ul style="list-style-type: none"> ► Dual dial arm mount provides increased adjustability - typically used with WT6400 Keyboard configs or devices with Extended Battery. ► Uses dial-to-fit design which is strong, durable, and easy to use. ► Velcro free design uses non-absorbent materials that can be wiped down. ► Includes Carrier and Large size Wrist Strap (SG-WT5X6-WMTDL-01). ► Black Dial and accent color on strap identify size as large. ► Strap length can be adjusted between 164 to 265 mm (approx 6.5 to 10.5") ► It is typical for each user to have their own wrist mount (for hygiene). 	
SG-WT5X6-WMTDX-01		Double Dial Wrist Mount (extra large strap)	<ul style="list-style-type: none"> ► Dual dial arm mount provides increased adjustability - typically used with WT6400 Keyboard configs or devices with Extended Battery. ► Uses dial-to-fit design which is strong, durable, and easy to use. ► Velcro free design uses non-absorbent materials that can be wiped down. ► Includes Carrier and Extra-Large size Wrist Strap (SG-WT5X6-WMTDX-01). ► Blue Dial and accent color on strap identify size as extra-large. ► Strap length is 375 mm (approx 14.75") ► This size strap is typically used in freezer environments where users may be wearing heavy jackets. ► It is typical for each user to have their own wrist mount (for hygiene). 	
SG-WT5X6-WSTDS-01		Replacement Double Dial Wrist Strap (small)	<ul style="list-style-type: none"> ► White Dial and accent color on strap identify size as small. ► Strap length can be adjusted between 128 to 191 mm (approx 5.0 to 7.5") 	

SG-WT5X6-WSTD01		Replacement Double Dial Wrist Strap (large)		<p>► Black Dial and accent color on strap identify size as large.</p> <p>► Strap length can be adjusted between 164 to 265 mm (approx 6.5 to 10.5")</p>
SG-WT5X6-WSTD01		Replacement Double Dial Wrist Strap (extra large)		<p>► Blue Dial and accent color on strap identify size as extra-large.</p> <p>► Strap length can be adjusted between 218 to 375 mm (approx 8.5 to 14.75")</p>





Wrist Mount - double Velcro strap

Part Number	Picture	Description	Notes	Required Items
SG-WT5X6-WMTVS-01 (small) SG-WT5X6-WMTVL-01 (large) SG-WT5X6-WMTVX-01 (extra large)		Wrist Mount with 2-Velcro Straps	<p>► Includes Carrier and two Velcro straps.</p> <p>► Strap lengths:</p> <ul style="list-style-type: none"> - Small, 290mm (~11.5 in) - Large, 340mm (~13.25 in) - Extra Large, 440mm (~17.25 in) <p>► It is typical for each user to have their own wrist mount (for hygiene).</p>	
SG-WT5X6-WSTVS-01 (small) SG-WT5X6-WSTVL-01 (large) SG-WT5X6-WSTVX-01 (extra large)		Replacement Double Velcro Straps for Wrist Strap	<p>► Strap lengths:</p> <ul style="list-style-type: none"> - Small, 290mm (~11.5 in) - Large, 340mm (~13.25 in) - Extra Large, 440mm (~17.25 in) 	




Other soft goods



Part Number	Picture	Description	Notes	Required Items
-------------	---------	-------------	-------	----------------

SG-WT5X6-CMPD-01		Comfort Pad for Wrist Mount	<ul style="list-style-type: none"> ► Optional Comfort Pad attaches to Wrist Mount to provide additional cushioning. ► Made with soft rubber. ► Pad may be preferred by users with larger arms. 	
SG-WT4027050-01R		Arm Sleeve (pack of 5)	<ul style="list-style-type: none"> ► Worn under WT6400 wrist mount if worker is in short-sleeved shirt and wants: <ul style="list-style-type: none"> - Extra sweat wicking/ personal layer - Extra comfort - Extra slip-resistance ► Material will not snag ► One size fits all ► Washable in mild detergent. Should be air dried. ► Pack of 5 Arm Sleeves 	
SG-WT5X6-HPMNT-01		Hip-mount Clip	<ul style="list-style-type: none"> ► Allows device to be worn on hip ► Will attach to clothing, user's belt, or optional Belt for Hip-mount Clip (11-08062-02R) 	
11-08062-02R		Belt for Hip-mount Clip	<ul style="list-style-type: none"> ► Belt is 2 inches wide ► Extends to 48 inches ► Has improved buckle and softer belt material 	
V6198DW (3rd party) * http://www.ultimacase.com		Belt Extender	<ul style="list-style-type: none"> ► Used to extend the Hip-mount belt (11-08062-02R) an additional 10 inches 	
Scanner Options and Accessories				
Ring Scanner (RS5000x - 2D Corded Imager)				
Part Number	Picture	Description	Notes	Required Items
RS5000X-TCFSSWR		RS5000x Scanner with Standard Finger Trigger	<ul style="list-style-type: none"> ► Uses SE4770 scan engine. ► Includes standard finger trigger for use over finger or light gloves. ► IP65 sealed ► Extended temperature spec down to -30C (-22°F) for freezer environments. 	
RS5000X-TCFSXWR		RS5000x Scanner with Large Finger Trigger	<ul style="list-style-type: none"> ► Uses SE4770 scan engine. ► Includes large finger trigger for use over heavy freezer gloves. ► IP65 sealed ► Extended temperature spec down to -30C (-22°F) for freezer environments. 	

SG-RS50X-TRGS-01		Replacement Trigger, Standard Size	<ul style="list-style-type: none"> ► Replacement standard finger trigger for use over finger or light gloves. ► Includes finger strap (SG-RS51-STRPN2-10 qty 1). 	
SG-RS50X-TRGX-01		Replacement Trigger, Large Size	<ul style="list-style-type: none"> ► Replacement large finger trigger for use over heavy freezer gloves. ► Includes finger strap with freezer grip (SG-RS50X-STRPX-01). 	
SG-RS51-STRPN2-10		Replacement Strap, Standard Size (pack of 10 straps)	<ul style="list-style-type: none"> ► Replacement finger strap used with Standard Trigger. ► NOTE: This is the same strap used with RS5100/RS6100 Single Trigger configurations. 	
SG-RS50X-STRPX-01		Replacement Strap, Large Size (single strap)	<ul style="list-style-type: none"> ► Replacement finger strap with freezer grip used with Large Trigger. 	

Ring Scanner (RS5000 - 2D Corded Imager)

Part Number	Picture	Description	Notes	Required Items
RS5000-LCFSWR		RS5000 Ring Scanner with short cable (for wrist mount)	<ul style="list-style-type: none"> ► Uses SE4710 scan engine. ► IP54 sealed ► Extended temperature spec down to -30C (-22°F) for freezer environments. 	
RS5000-LCFLWR		RS5000 Ring Scanner with long cable (for hip mount)	<ul style="list-style-type: none"> ► Uses SE4710 scan engine. ► IP54 sealed ► Extended temperature spec down to -30C (-22°F) for freezer environments. 	
SG-NGRS-SFSVS-01R		RS5000 Spare Ring Scanner Strap (Short)	<ul style="list-style-type: none"> ► Short finger strap - 6" long ► It is typical for each user to have their own ring scanner strap (for hygiene). ► This is the same strap that is included on each RS5000. 	





SG-RS419-FGSTP-02R		RS4000/RS5000/ RS409/RS419 Spare Ring Scanner Strap (Long)	<ul style="list-style-type: none"> ► Improvements include a new connection between the velcro and fabric used as part of the accessory. ► Long finger strap - 7.8" long ► It is typical for each user to have their own ring scanner strap (for hygiene). 	
SG-NGRS-TRGASR-01R		RS5000 Replacement Trigger Assembly	<ul style="list-style-type: none"> ► Uses same design as RS419 Trigger (SG-RS419-TRGAS-01R), but doesn't include laser warning label on trigger button. 	

Ring Scanner (RS5100/RS6100 - 2D Cordless Bluetooth Imager) (see RS5100 or RS6100 Accessories document for additional accessories)






CBL-RS5X6-ADPWT-01		Corded Adapter / Battery Eliminator for WT6X series	<ul style="list-style-type: none"> ► Adapter acts as a battery eliminator and allows RS5100/RS6100 to be powered directly from the WT6000/WT6300/WT6400. ► May provide simpler back room operations by not requiring separate battery charging hardware for the RS5100/RS6100. May also prevent loss/misplacement of RS5100/RS6100 by having it tethered to the WT6X. ► Adapter only provides power to scanner. Scanner communicates to the WT6X device via Bluetooth. 	
--------------------	---	--	---	--

Ring Scanner (RS6000 - 2D Cordless Bluetooth Imager) (see RS6000 Accessories document)

Ring Scanner (RS4000 - 1D Corded Laser)

Part Number	Picture	Description	Notes	Required Items
RS4000-HPCSWR		RS4000 Ring Scanner with short cable (for wrist mount)	<ul style="list-style-type: none"> ► Uses SE965 scan engine with Adaptive Scanner for longer read ranges (near contact to 200 inches). ► Extended temperature spec down to 30C for freezer environments. 	
RS4000-HPCLWR		RS4000 Ring Scanner with long cable (for hip mount)	<ul style="list-style-type: none"> ► To be discontinued 6/2025 - see PMB-11589. ► Uses SE965 scan engine with Adaptive Scanner for longer read ranges (near contact to 200 inches). ► Extended temperature spec down to 30C for freezer environments. 	
SG-RS419-FGSTP-02R		RS4000/RS5000/ RS409/RS419 Spare Ring Scanner Strap (Long)	<ul style="list-style-type: none"> ► Improvements include a new connection between the velcro and fabric used as part of the accessory. ► Long finger strap - 7.8" long ► It is typical for each user to have their own ring scanner strap (for hygiene). ► This is the same strap that is included on each RS419. 	
21-93022-03R		RS4000/RS409/RS419 Spare Ring Scanner Strap (Short)	<ul style="list-style-type: none"> ► Improvements include a new connection between the velcro and fabric used as part of the accessory. assembly over previous version. ► Short finger strap - 6" long ► It is typical for each user to have their own ring scanner strap (for hygiene). ► This is the same strap that is included on each RS409. 	

Headset/Audio Accessories

Wired Headsets and Audio Accessories				
Part Number	Picture	Description	Notes	Required Items
See HS2100-HS3100 Accessories Document		HS2100 Rugged Wired Headset	<ul style="list-style-type: none"> ► Built to handle the everyday inevitable drops ► Dustproof, sprayproof and waterproof ► Ready for the freezer and outdoor subzero temperatures ► Feather-light for extraordinary comfort ► Noise cancellation for a superior voice experience in the noisiest environments ► Detachable swivel boom minimizes costs. ► Swivelling boom mutes microphone allowing uses to prevent voice pick applications from recognizing non-voice pick conversations. ► User-replaceable pads and windscreens maximize comfort and hygiene 	<p><u>Requires one of the following cable options:</u></p> <p>(1) HS2100 to WT6X Cable (CBL-HS2100-12S1-01)</p> <p>OR</p> <p>(2) Quick Disconnect Headset cable (CBL-HS2100-QDC1-02) AND WT6X to Quick Disconnect Adapter Cable (CBL-NGWT-AUQDST-02 or CBL-NGWT-AUQDLG-02)</p> <p>See HS2100/HS3100 Accessories Document for additional headset accessories</p>
CBL-HS2100-12S1-02		HS2100 Headset to WT6X cable	<ul style="list-style-type: none"> ► Connects HS2100 directly to WT6000/WT6300/WT6400. ► 43" long straight cable ► Includes one clip for attaching to clothing. Additional clips can be purchased separately. ► Uses improved strain relief design vs. CBL-HS2100-12S1-01. 	
CBL-HS2100-12S1-01		HS2100 Headset to WT6X cable	<ul style="list-style-type: none"> ► Connects HS2100 directly to WT6000/WT6300/WT6400. ► 43" long straight cable ► Includes one clip for attaching to clothing. Additional clips can be purchased separately. 	
CBL-NGWT-AUQDLG-02		Headset Adapter Cable (long cable)	<ul style="list-style-type: none"> ► Connects wired headsets with Quick Disconnect connector (i.e. HS2100 / RCH50 RCH51, BlueParrot, Voxware, and Eartec headsets) to WT6000/WT6300/WT6400. ► Cable is used when WT6X is worn on the hip. ► Provides additional strength on Quick Disconnect connector vs. CBL-NGWT-AUQDLG-01. 	
25-129938-02R		Headset Training Y cable	<ul style="list-style-type: none"> ► To be discontinued 6/2025 - see PME 11589. ► Connects two Quick Disconnect wired headsets to the WT6X. ► Extra cable to plug in a second headset or external speakers for training or performing a demo. 	
Bluetooth Headsets and Audio Accessories				
NOTE: Bluetooth headsets with PTT function not supported by Zebra PTT Express application. Check with Engineering to verify compatibility with Zebra PTT Pro application.				
Part Number	Picture	Description	Notes	Required Items

various (3rd party) *		Stone Mountain BluSkye Bluetooth Remote Speaker Mic (RSM)	<ul style="list-style-type: none"> ▶ Bluetooth speaker-microphone designed to work with different walkie talkie style Push-to-Talk applications, including Zebra PTT Pro (check with Zebra PTT Pro engineering team for current device/OS support). ▶ Device is ruggedized, MIL-STD 810G and IP68. 	
--------------------------	--	---	--	--









<http://stonemountainltd.com>




Misc

Part Number	Picture	Description	Notes	Required Items
MISC-WT5X6-MCLT-01		Replacement Cleat	<ul style="list-style-type: none"> ▶ To be discontinued 6/2025 - see PMB-11589. ▶ Spare/replacement Wrist Mount Cleat for back of device. ▶ Includes 4 Torx T6 screws for mounting to rear of device. 	
CBL-NGWT-HDVBAP-01		Vibrating Cable	<ul style="list-style-type: none"> ▶ Connects to WT6400 and provides additional haptic feedback to user. ▶ Cable is normally attached to user's wrist ▶ Can be used in noisy environments or for hearing impaired users. 	
MISC-WT5X6-SCRN-05		Screen Protector (pack of 5)	<ul style="list-style-type: none"> ▶ Optional/add-on screen protector for the WT5400/WT6400. 	

Power Cords/Power Supplies

Part Number	Picture	Description	Notes	Required Items
CBL-DC-388A1-01		DC Power Cord	<ul style="list-style-type: none"> ▶ Used along with Power Supply PWR-BGA12V50W0WW to power Single Slot Cradle and 4-Slot Battery Charger. ▶ Cable length is 1.8 meters 	
PWR-BGA12V50W0WW		Power Supply	<ul style="list-style-type: none"> ▶ Used to power Single Slot Cradle and 4-Slot Battery Charger. ▶ 100-240 VAC, 12V, 4.16A, 50W ▶ Provides US DOE Level VI compliance for power efficiency. 	<ul style="list-style-type: none"> ▶ DC Line Cord (CBL-DC-388A1-01) ▶ AC Line Cord (23844-00-00F or country specific version)

KIT-PWR-12V50W		Power Supply Kit	<ul style="list-style-type: none"> ► Includes Power Supply (PWR-BGA12V50W0WW) and DC Line Cord (CBL-DC-388A1-01) 	► AC Line Cord (23844-00-00R or country specific version)
CBL-DC-383A1-01		DC Line Cord	<ul style="list-style-type: none"> ► Used to power Snap-On USB/Charge Cable with Power Supply PWR-BUA5V16W0WW ► Cable length is 6 ft. 	
PWR-BUA5V16W0WW		Power Supply	<ul style="list-style-type: none"> ► Used with Snap-On USB/Charge Cable ► 100-240VAC, 5.4V, 3A, 16W ► Meets US DOE Level VI efficiency standard 	DC Line Cord (CBL-DC-383A1-01) and AC Line Cord (50-16000-182R)
CBL-DC-381A1-01		DC Power Cord	<ul style="list-style-type: none"> ► Used to power 5-Slot, 10-Slot, 20-Slot Cradles when using Level VI Efficiency power supply (PWR-BGA12V108W0WW) 	
CBL-DC-382A1-01		DC Power Cord	<ul style="list-style-type: none"> ► Used with Power Supply PWR-BGA12V108W0WW to power 5-Slot, 10-Slot, 20-Slot Cradles ► This cable includes a black extension release latch/clip that is needed when powering legacy non-ShareCradle design multi-slot cradles. This cable can be used instead of CBL-DC-381A1-01, if needed. ► CBL-DC-381A1-01 is the preferred cable to use. 	
PWR-BGA12V108W0WW		Power Supply	<ul style="list-style-type: none"> ► Used to power 5-Slot, 10-Slot, 20-Slot Cradles ► 100-240 VAC, 12V, 9A, 108W ► Provides US DOE Level VI compliance for power efficiency. 	<ul style="list-style-type: none"> ► DC Line Cord (CBL-DC-381A1-01) ► AC Line Cord (23844-00-00R or country specific version)
23844-00-00R		AC Line Cord	<ul style="list-style-type: none"> ► Used to power all cradles. ► This AC Line Cord is for use in North America. See the AC Line Cords by Country TAG for comparable line cords to use in other countries. 	
50-16000-182R		AC Line Cord	<ul style="list-style-type: none"> ► Used with PWR-BUA5V16W0WW to power Snap-on charging cables. ► This AC Line Cord is for use in North America. See the AC Line Cords by Country TAG for comparable line cords to use in other countries. 	
Batteries				
Part Number	Picture	Description	Notes	Required Items

<p>BTRY-WT5X6-35MA-01</p> <p>BTRY-WT5X6-35MA-IN (for use in India)</p>		<p>Spare Standard Capacity Battery with PowerPrecision+ (3500 mAh)</p> 	<ul style="list-style-type: none"> ▶ Supports operation between -20C/-4F and 50C/122F. ▶ Designed, manufactured & tested to meet rigorous controls & standards ▶ Premium-grade cells with higher capacity & longer life cycle ▶ Designed to help prevent overcharging & electrical shock ▶ Strong & robust housing for optimal performance & durability ▶ Information available: <ul style="list-style-type: none"> - Available charge status - Total charge accumulated on the battery - Basic state of health 	
<p>BTRY-WT5X6-50MA-01</p> <p>BTRY-WT5X6-50MA-IN (for use in India)</p>		<p>Spare Extended Capacity Battery with PowerPrecision+ (5000 mAh)</p> 	<ul style="list-style-type: none"> ▶ Supports WT6400 operation between 30C/-22F and 50C/122F, WT5400 operation between -20C/-4F and 50C/122F. ▶ Designed, manufactured & tested to meet rigorous controls & standards ▶ Premium-grade cells with higher capacity & longer life cycle ▶ Designed to help prevent overcharging & electrical shock ▶ Strong & robust housing for optimal performance & durability ▶ Information available: <ul style="list-style-type: none"> - Available charge status - Total charge accumulated on the battery - Basic state of health 	